

Talento 111 mini & 211 mini

INSTALLATION & OPERATING INSTRUCTIONS

PRODUCT/ORDER CODE

Talento 111mini	single channel	16 Amps
Talento 211mini	single channel	16 Amps
Talento 111mini	24 hour synchronous timeswitch.	
Talento 211mini	24 hour quartz with reserve timeswitch	

This product is suitable for din-rail mounting.



The 24 hour dial has 48 captive tappets. Each tappet switches the output for 30 minutes

INSTALLATION – GENERAL NOTES:

INSTALLATION SHOULD BE CARRIED OUT IN ACCORDANCE WITH THE CURRENT EDITION OF THE I.E.E. WIRING REGULATIONS. ALL TERMINALS ARE SUITABLE FOR FIXED CABLES, AND FOR FLAXIBLE CABLES OR CORD. SWITCH THE SUPPLY OFF AT THE MAINS. MEANS OF DISCONNECTION FROM THE SUPPLY HAVING AT LEAST 3mm CONTACT SEPARATION IN ALL POLES MUST BE INCORPORATED IN THE FIXED WIRING MAINS SUPPLY

SETTING UP

ROTATE DIAL UNTIL CURRENT TIME LINES UP WITH ARROWHEAD ON FRONT OF TIMER BODY UNIT , TO SET ON/OFF TIMES, MOVE ALL TAPPETS TO POSITION **I** BETWEEN ON AND OFF TIMES REQUIRED POSITION i.e. TO SET ON AT 8.00 a.m. AND OFF AT 11.00 a.m. MOVE ALL TAPPETS TO OUTER POSITION, SET ANY OTHER ON/OFF TIMES IN A SIMILER MANNER.


MANUAL SWITCH

THE MANUAL SWITCH CAN BE MOVED TO OVERRIDE THE TIMED SELECTION:

IN POSITION **I** THE TIMESWITCH IS PERMANENTLY ON IRRESPECTIVE OF TAPPET POSITIONS.

IN **CLOCK FACE** POSITION THE TIMESWITCH IS OPERATING ON TIMED CONTROL AND WILL SWITCH ON AND OFF AS DETERMINED BY TAPPET POSITIONS.

talento 111 mini, talento 211 mini



talento 111 mini, talento 211 mini

