



File E62405SP

Vol 1

Auth. Page 1

Issued: 1982-01-06

Revised: 2012-12-06

FOLLOW-UP SERVICE PROCEDURE  
(TYPE R)

UNLISTED COMPONENT

ATTACHMENT PLUGS, FUSELESS  
(AXUT3,AXUT9)

Manufacturer: SEE ADDENDUM FOR MANUFACTURER LOCATIONS

68781 (Party Site)  
Applicant: VOLEX (ASIA) PTE LTD  
(337951-004) 35 TAMPINES ST 92  
SINGAPORE 528880 SINGAPORE

This Follow-Up Service Procedure authorizes the above Manufacturer(s) to use the marking specified by UL LLC, or any authorized licensee of UL LLC, including the UL Contracting Party, only on products when constructed, tested and found to be in compliance with the requirements of this Follow-Up Service Procedure and in accordance with the terms of the applicable service agreement with UL Contracting Party and any applicable Service Terms. The UL Contracting Party for Follow-Up Services is listed on addendum to this Follow-Up Service Procedure ("UL Contracting Party"). UL Contracting Party and UL LLC are referred to jointly herein as "UL."

UL further defines responsibilities, duties and requirements for both Manufacturers and UL representatives in the document titled, "UL Mark Surveillance Requirements" that can be located at the following web-site: <http://www.ul.com/fus> and in the document titled "UL and Subscriber Responsibilities" that can be located at the following website: <http://www.ul.com/responsibilities>. Manufacturers without Internet access may obtain the current version of these documents from their local UL customer service representative or UL field representative. For assistance, or to obtain a paper copy of these documents or the applicable Service Terms, please contact UL's Customer Service at <http://www.ul.com/global/eng/pages/corporate/contactus>, select a location and enter your request, or call the number listed for that location.

The Applicant and the specified Manufacturer(s) in this Follow-Up Service Procedure must agree to receive Follow-Up Services from UL Contracting Party. If your applicable agreement is a Global Services Agreement ("GSA") with an effective date of January 1, 2012 or later and this Follow-Up Service Procedure is issued on or after that effective date, the Applicant and the specified Manufacturer(s) will be bound to a Service Agreement for Follow-Up Services upon the earliest by any Subscriber of use of the prescribed UL Mark, acceptance of the factory inspection, or payment of the Follow-Up Service fees which will incorporate such GSA, this Follow-Up Service Procedure and the Follow-Up Service Terms which can be accessed by clicking here: <http://www.ul.com/contracts/Terms-After-12-31-2011>. In all other events, Follow-Up Services will be governed by and incorporate the terms of your applicable service agreement and this Follow-Up Service Procedure.

It is the responsibility of the Manufacturer to make sure that only the products meeting the aforementioned requirements bear the authorized Marks of UL LLC, or any authorized licensee of UL LLC.

This Follow-Up Service Procedure contains information for the use of the above Manufacturer(s) and representatives of UL and is not to be used for any other purpose. It is provided to the Manufacturer with the understanding that it will be returned upon request and is not to be copied in whole or in part.

This Follow-Up Service Procedure, and any subsequent revisions, is the property of UL and is not transferable. This Follow-Up Service Procedure contains confidential information for use only by the above named Manufacturer(s) and representatives of UL and is not to be used for any other purpose. It is provided to the Subscribers with the understanding that it is not to be copied, either wholly or in part unless specifically allowed, and that it will be returned to UL, upon request.

Capitalized terms used but not defined herein have the meanings set forth in the GSA and the applicable Service Terms or any other applicable UL service agreement.

UL shall not incur any obligation or liability for any loss, expense or damages, including incidental, consequential or punitive damages arising out of or in connection with the use or reliance upon this Follow-Up Service Procedure to anyone other than the above Manufacturer(s) as provided in the agreement between UL LLC or an authorized licensee of UL LLC, including UL Contracting Party, and the Manufacturer(s).

UL LLC has signed below solely in its capacity as the accredited entity to indicate that this Follow-Up Service Procedure is in compliance with the accreditation requirements.

William R. Carney  
Director  
North American Certification Program

LOCATION

(106395-001) 433003 (Party Site)  
VOLEX CABLE ASSEMBLY (SHENZHEN) CO LTD  
VOLEX BLDG  
1173 SHENHUI RD  
BAO'AN, HENGGANG  
SHENZHEN  
GUANGDONG 518115 CHINA  
Factory ID: SM or HG  
UL Contracting Party for above site is: UL AG

(221809-001) 31812 (Party Site)  
P T VOLEX INDONESIA  
KAWASAN INDUSTRI  
SEKUPANG  
BATAM RIAU  
. INDONESIA  
Factory ID: B  
UL Contracting Party for above site is: UL AG

(342882-001) 67739 (Party Site)  
VOLEX CABLE ASSEMBLY (VIETNAM) CO LTD  
D-5B THANG LONG INDUSTRIAL PARK  
DONG AHH DISTRICT  
HANOI VIET NAM  
Factory ID: VH  
UL Contracting Party for above site is: UL AG

(788163-001) 171879 (Party Site)  
VOLEX INTERCONNECT (INDIA) PVT LTD  
22-1A 1ST ST  
KHAZURA GARDEN  
NEELANGARAI  
CHENNAI TN 600041 INDIA  
Factory ID: VC  
UL Contracting Party for above site is: UL India Private Limited

LOCATION

(902299-002) 200782 (Party Site)  
VOLEX DE MEXICO S A  
AVE 32 SUR NUM 8950  
INTERIOR EDIFICIO G1, D, E, F  
PARQUE INDUSTRIAL LA MESA, FRACC RUBIO  
22650 TIJUANA  
BC MEXICO

Factory ID: TI  
UL Contracting Party for above site is: UL AG

(918517-001) 196799 (Party Site)  
VOLEX CABLE ASSEMBLY (ZHONGSHAN) CO  
LTD  
ZHONGSHAN TORCH HI TECH IND DEV ZONE  
2 SINTA N ST  
ZHONGSHAN  
GUANGDONG 528437 CHINA

Factory ID: SM1 OR SMI  
UL Contracting Party for above site is: UL AG

## INDEX

## ATTACHMENT PLUG:

Models	Section	Report Date
Unlisted component, Attachment-Plug Cap! Cat. No.ME301.	1	1976-12-23

## NEMA CONFIGURATION

Cat. No.	Config.	Cord AWG	Electrical A/V	Sec.	Fig.	USU	CNU
ME301, -D, - P, -S, -R, - RP	1-15	20,18,17,16/2	7,10,10,13/125	2	1,1A	Yes	Yes
230619-001	1-15	18/2	5/125	2	1B	Yes	Yes
USJ15	1-15	18,16/2	7,10,13/125	2	1	Yes	Yes
ME302, -B, - P	1-15	18,17,16/2	10,12,13/125	2	2	Yes	Yes
ME302GR	1-15	18,17,16/2	10,12,13/125	2	3	Yes	Yes
US115LS, - LPS, -S	1-15	18,16/2	10,13/125	2	4,6	Yes	Yes
926	1-15	18,16,14/2	10,13,15/125	2	7	Yes	Yes
926SR	1-15	18,16,14/2	10,13,15/125	2	11,13,14	Yes	Yes
926NPSR	1-15	18,16,14/2	10,13,15/125	2	16	Yes	Yes
926BSR	1-15	18,16,14/2	10,13,15/125	2	11,13,14,16	Yes	Yes
<b>DS15EPS2</b>	<b>1-15</b>	<b>18,17,16/2</b>	<b>10,12,13/125</b>	<b>2</b>	<b>21</b>	<b>Yes</b>	<b>Yes</b>
US115SC, - PSC	1-15	18/2	7/125	3	16	Yes	Yes
US15B, -P	1-15	18,16,14/2	10,13,15/125	2	4	Yes	Yes
US15S2	1-15	18/2	10/125	2	11,17	Yes	Yes
USJ15B	1-15	18/2	10/125	2	4	Yes	Yes
MP128 (EMI)	1-15	18/2	10/125	3	5	Yes	Yes
VP129 (EMI)	1-15	18/2	10/250	3	14	Yes	Yes
US515SC (EMI)	5-15	16/3	13/125	3	21	Yes	Yes
185, -F	5-15	18,16,14/3	10,13,15/125	2	--	Yes	No
CX-490, -495	5-15	14,12,10/3	15,20,30/250	2	8	Yes	No
3323 (Hosp)	5-15	16,14/3	13,15/125	3	11,12	Yes	Yes
3317	5-15	18,16/3	10,13/125	3	13	Yes	Yes
AEC60 (Hosp)	5-15	18,16,14,12/3	10,13,15,15/125	3	15	Yes	Yes
PS204, -B, - D	5-15	18,17,16,14/3	10,12,13,15/125	3	1	Yes	Yes
PS204A	5-15	18,17,16,14/3	10,12,13,15/125	3	3	Yes	Yes
US515A, USI515A	5-15	18,16,14/3	10,13,15/125	3	17	Yes	Yes
PS206	5-15	18,16,14/3	10,13,15/125	3	2	Yes	Yes
PS206A	--	18,16	10,13	3	--	Yes	Yes
PS515	5-15	18,16,14,12/3	10,13,15,20/125	3	10	Yes	Yes
MP204	5-15	18,16,14/3	10,13,15,15/125	3	4	Yes	Yes
USD15A, - S15A	5-15	18,16/3	10,13/125	3	9	Yes	Yes
PS520	5-20	18,16, 18,16, 14,12/314,12/3	10,13, 18,20/125	3	10	Yes	Yes

## ATTACHMENT PLUG: (Cont'd)

## NEMA CONFIGURATION

Cat. No.	Config.	Cord AWG	Electrical A/V	Sec.	Fig.	USU	CNU
1541	L5-20	18,16,14/3	10,13,15/125	3	20	Yes	No
VS205A	6-15	18,16,14/3	10,13,15/250	3	8	Yes	Yes
VS205S	6-15	18,16,14/3	10,13,15/250	3	Ill.55,56	Yes	Yes
PS615	6-15	18,16,14,12/3	10,13,15,20/250	3	10	Yes	Yes
PS620	6-20	18,16,14,12/3	10,13,18,20/250	3	10	Yes	Yes
VS207A	6-20	14,12/3	15,20/250	3	6	Yes	Yes
VS208A	6-30	12/3	25/250	3	7	Yes	Yes
PL3001	1-15	18/2	10/125	3	23	Yes	Yes
PL3007	1-15	14/3	15/125	3	--	Yes	Yes
PS206A	5-15	18,16/3	10,13/125	3	24	Yes	Yes
US650A, US650A (A.C.1)	6-50	12/3	25/250	3	25,33	Yes	Yes
US15S3	5-15	18/3	10/125	3	Ill.51	Yes	Yes
MA115VPS2	1-15	18, 16/2	10,15/125	9	Ill.1	Yes	Yes
USL620PS3	L6-20	14,12/3	15,20/250	3	26	Yes	Yes
VPUS15S3	5-15	18,16/3	10,13/125	3	27	Yes	Yes
US515NGA3, US515EGA3, US515SGA3, US515WGA3	5-15	18,16,14	10,13,15/125	3	28	YES	YES
US515BTA3	5-15	18,16	10,13/125	3	29	YES	YES
VPUS15DS3	5-15	18,16	10,13/125	3	-	YES	YES
US15GPS2	1-15	17,16	12,13/125	2	9	YES	YES
USJ15TS3	5-15	18,16,14	10,13,15/125	3	30	YES	YES
US115VPS2	1-15	18,17	10,12/125	2	13	YES	YES
US115DPS2	1-15	17	12/125	2	10	YES	YES
RA115GRP	1-15	18,17,16	10,12,13/125	2	11	YES	YES
USL520PS3	L5-20	18,16,14,12	10,13,15,20/125	3	31	YES	YES
PS520A	5-20	12	20/125	3	32	YES	YES
US115VS2	1-15	18,17	10,12/125	2	12	YES	YES
VPUS15S2	1-15	18/2	10/125	2	14	YES	YES
USD15GPS2	1-15	18,17,16/2	10,12,13/125	2	15	YES	YES
USD115PS2	1-15	17/2	12/125	2	16	YES	YES
APUS15S3	5-15	18,16/3	10,13/125	3	34	YES	YES
DS15PS2	1-15	18, 17, 16/2	10,12,13/125	2	17	YES	YES
ME301SH	1-15	18	10/125	2	18	YES	YES
APUS15S2	1-15	18/2	10/125	2	19	YES	YES
US15PA2	1-15	18/2	10/125	2	20	YES	YES
US520A3	5-20P	12/3	20/125	3	35,36	YES	YES
US15TS2	1-15	18/2	10/125	2	22	YES	YES
DS15JPS2	1-15P	18,17,16/2	10,12,13/125	2	23	YES	YES
HO515S3	5-15P	16/3	13/125	3	37	YES	-
MFUS15S2	1-15	18/2	2.5,7/125	2	24	YES	YES
AP7J34	1-15	18/2	10/125	2	25	YES	YES
DLUS15S3	5-15	18/3	7/125	9	1	YES	YES
VNUS15S3	5-15	18,16/3	2.5,10,13/125	2	26	YES	YES
VNUS15FS3	5-15	18/3	2.5,10/125	2	--	YES	YES
VNUS15S2	1-15	18/2	7, 10/125	2	27	YES	YES
<b>USL515PS3</b>	<b>L5-15</b>	<b>14/3</b>	<b>15/125</b>	<b>3</b>	<b>38</b>	<b>YES</b>	<b>YES</b>

Note: (A.C.1) - ALTERNATE CONSTRUCTION NO. 1.

## IEC CONFIGURATION

Cat. No.	Config.	Cord AWG	Electrical A/V	Sec.	Fig.	USU	CNU
PS25A	C14	18/3	10/250	5	1	YES	YES
PS25	C14	18/3	10/250	5	2	YES	YES
SSD10A	C14	18,16/3	10,13/250	5	3	YES	YES
3318-M3	C14	18,16/3	10,13/250	5	4	YES	YES
3321A,-B	C14	18,16/3	10,13/250	5	4	YES	YES
3322A,-B	C14	18,16/3	10,13/250	5	4	YES	YES
APC14	C14	18/3	10/250	5	6	YES	YES
VAC14A,-S	C14	18/3	10/250	5	9	YES	YES
VAC14BS	C14	16/3	13/250	5	9	YES	YES
VAC14LS	C14	16/3	10,13/125 or 250	5	Ill,32	YES	YES
		14/3	15,16/125 or 250				
94110/2	EuroPlug	18/2	2.5/250	5	5	YES	YES
201492-1	C14/C7(2)	18/2	7/250	5	7,8	YES	YES
VSC20	C20	16,14,12/3	13,16,20/250	5	10	YES	YES
PL3004	C14	16/3	13/125 or 250	5	11	YES	YES
VAC20S	C20	16,14/3	13,16/125 or 250	5	12	YES	YES
VAC20A	C20	16,14/3	13,15,16/125 or 250	5	20	YES	YES
VAC14KC	C14	18,16/3	10,13/125 or 250	5	21	YES	YES
VAC20KC	C20	14/3	16/125 or 250	5	22	YES	YES
VAC20BS	C20	12/3	20/125 or 250	5	23	YES	YES
VAC14LA	C14	18,16,14/3	10,13,15/125 or 250	5	24	YES	YES
VAC20AD	C20	14,12/3	16,20/125 or 250	5	25	YES	YES
VAC14KAL	C14	18,16/3	10,13/125 or 250	5	26	YES	YES
VAC14KAR	C14	18,16/3	10,13/125 or 250	5	27	YES	YES
VAC20KAR	C20	16,14,14/3	13,15,16/125 or 250	5	28	YES	YES
VAC20KAL	C20	16,14,14/3	13,15,16/125 or 250	5	29	YES	YES
SMC14LA	C14	18,16/3	10,13/125 or 250	5	30	YES	YES
VNC14S	C14	18,17,16/3	10,12,13/125 or 250	5	31	YES	YES
*VAC14SS	C14	18/3	10/250	5	32	YES	YES

## CORD CONNECTOR BODIES:

## NEMA CONFIGURATION

Cat. No.	Config .	Cord AWG	Electrical A/V	Sec.	Fig.	CUL
US115RPS	1-15	18/2	10/125	7	1	Yes
US515RP	5-15	18/3	10/125	7	2	Yes
US515RS, US515RS (A.C.1)	5-15	18,16,14/3	10,13,15/125	4	30,51	Yes
AEC-212, AEC-202,- 210,	5-15	18,16,14/3	10,13,15/125	4	32	Yes
28-9170	1-15	18,16,14/3	10,13,15/125	4	32	Yes
CN-4008	5-15	16, 14/3	13,15/125	4	38	Yes
PH-161	1-15	18,16,14/2	10,13,15/125	4	44,45, 46	No
US515RP-A	5-15	18/3	10/125	7	3	Yes

Note: (A.C.1) - ALTERNATE CONTRUCTION NO. 1.

## IEC CONFIGURATION

Cat. No.	Config.	Cord AWG	Electrical A/V	Sec.	Fig.	CUL
PS625,-A,-LA	C13	18,16,14/3	10,13,15/125	4	1	Yes
PS309,-P	C1	18/2	7/125	4	2	Yes
*M1625	C13	18,16/3	10,13/125 or 250	4	3,3A	Yes
VIC13A	<b>C13</b>	<b>18,16/3</b>	<b>10,13/125 or 250</b>	<b>4</b>	<b>3C</b>	
<b>V1625</b>	<b>C13</b>	<b>18,17,16/3</b>	<b>10,12,13/125 or 250</b>	<b>4</b>	<b>3, 3A</b>	<b>Yes</b>
V1625BS	C13	16,14,14/3	13,15,16/125 or 250	4	3B	Yes
VAC13KS	C13	18/3 16/3 14/3	10/125 or 250 13/125 or 250 15/125 or 250	4	3D	Yes
M1250A,-P	C7	18/2	7/250	4	4	Yes
M1250R	C7	18/2	7/250	4	4A	Yes
MS212,-A	C9	18/2	10/125	4	5	Yes
MS225	C17	18/2	10/125	4	6	Yes
VAC17S,-BS	C17	18,16,14/2	10,13,15/125	4	6A	Yes
PIC17BS	C17	14/2	15/125	4	6B	Yes
YAC17S, PIC17S	C17	18/2	10/125	4	6A	Yes
VAC17A	C17	16/2	10,13/125	4	6C	Yes
M2825	C15, C15A	18,16/3	10,15 (HPN) /125	4	7	Yes
VAC15A	C15	16,14/3	13, 16/125 or 250	4	52	Yes
VAC15S	C15	18,16,14/3	10,13,15/250 (HPN)	4	7	Yes
VAC15BS	C15	18,16,14/3	10,13,15/250	4	7	Yes
		18	10/125 (SJ)			
25AC5, 25ARAC5	C5	18/3	2.5,7/125 or 250	4	8	Yes
VAC5S,-AL,-AR	C5	18/3	2.5,7/125 or 250	4	8	Yes
V1625LA	C13	18,16,14/3	10,13,15/125 or 250	4	9	Yes
V1625A	C13	18,16/3	10,13/125 or 250	4	9	Yes
V1625BA	C13	16,14/3	13,15/125 or 250	4	9A	Yes



## CORD CONNECTOR BODIES CON'T:

## IEC CONFIGURATION

Cat. No.	Config.	Cord AWG	Electrical A/V	Sec.	Fig.	CUL
AVLC13	C13	18,16,14,14/3	10,13,15,16/125 or 250	4	9B	Yes
AVRC13	C13	18,16,14/3	10,13,15/125 or 250	4	9B	Yes
3318-F3	C13	18,16/3	10,13/125	4	10	Yes
3319A,-B	C13	18,16/3	10,13/125	4	10	Yes
3320A,-B	C13	18,16/3	10,13/125	4	10	Yes
VSC15,VRC15,VLC15	C15	18,17,16,14/3	10,10,13,15/250	4	11	Yes
VSC13,VRC13,VLC13	C13	18,17,16,14/3	10,10,13,15/250	4	11	Yes
VSCC13	C13	18/3	10/250	4	11A	Yes
VSC19,VRC19,VLC19	C19	18,16,14,12/3	10,13,16,20/250	4	12	Yes
VSCC19	C19	18,16,14,12/3	10,13,16,20/250	4	--	Yes
8393	Spec.	18/3	10/125	4	13	Yes
HS10S,-U	C13	18,16/3	10,13/250	4	14	Yes
HS10A,-U	C13	18,16/3	10,13/250	4	15	Yes
Z357316	C17	18/2	10/125	4	--	Yes
Z357318	C13	18/2	10/250	4	16	Yes
16SCI	C19	16/3	13/250	4	17	Yes
AP19M18	C19	14/3	15/125	8	1	Yes
APC13	C13	18,16/3	10,13/250	4	18	Yes
APC13S	C13	18/3	10/250	4	31	Yes
APC5A	C5	18/3	10/125	4	19	Yes
APC5M	C5	18/2	10/125	4	20	Yes
APC7M	C7	18/2	2.5/125	4	29	Yes
APC5S, -5SM	C5	18/3	10/125	4	21	Yes
VAC7PS	C7	18/2	7/125	4	23	Yes
VAC7S, SZC7S	C7	18/2	2.5,7/125 or 250	4	23	Yes
VAC7A	C7	18/2	7/125	4	24	Yes
APC7S	C7	18/2	2.5/125 or 250	4	25	Yes
APC7Q	C7	18/3 (Functional Ground)	2.5/125	4	35	Yes
VAC19	C19	16,14,12/3	13,15,20/250	4	26	Yes
VAC19A, VAC19LA	C19	16,14,12/3	13,15,20/125 or 250	4	<b>65</b>	Yes
APC5SP, -SF	C5	18/3	2.5/250	4	27	Yes
CN-4001	C17	18/2	10/125	4	28	Yes
CN-4002	C13 (Special Use)	16/3	13/125 or 250	4	36	Yes
APC13F	C13 (Special Use)	18,16/3	10,13/125	4	37	Yes
APC13G	C13 (Special Use)	18/3	10/125 or 250	4	39	Yes
APC13H	C13 (Special Use)	18/3	10/125 or 250	4	53	Yes
DLC7U2	C7	18/2	2.5/125	4	-	Yes
DLC5U3	C5	18	2.5/125	4	-	Yes
AP7M16	C7	18	2.5/125	4	-	Yes
APC13FH	C13 (Special Use)	16/3	13/125	4	62	Yes

## CORD CONNECTOR BODIES CON'T:

## IEC CONFIGURATION

Cat. No.	Config.	Cord AWG	Electrical A/V	Sec.	Fig.	CUL
VCC13	C13	18/3	10/125	4	40	Yes
VAC19KS	C19	14, 14,12/3	15,16,20/125 or 250	4	41	Yes
SOC7S	C7	18/2	7/125	4	42	Yes
APC13GH	C13	18/3	10/125	4	43	Yes
HPC13A	C13	18,16/3	10,13/250	4	47	Yes
DLC7E2	C7	18/2	2.5/125	4	48	Yes
DLC5E3	C5	18/3	2.5/125	4	49	Yes
V1625AT	C13	18/3	10/250	4	50	Yes
VCC7S	C7	18/2	3,7/125 or 250	4	54	Yes
VCC5S	C5	18/3	2.5/125 or 250	4	55	Yes
APC7H	C7	18/3 (Functional Ground)	2.5/125	4	56	Yes
VCC5AR	C5	18/3	2.5/125 or 250	4	57	Yes
VCC13A	C13	18/3	10/125 or 250	4	58	Yes
V1625H	C13	18,16/3	10,13/125 or 250	4	59	Yes
VAC19H	C19	14,14,12/3	15,16,20/125 or 250	4	60	Yes
APC7K	C7	18/2	2.5/125	4	61	Yes
VCC7	C7	18/2	7/125 or 250	4	63	Yes
HOC13S	C13	16/3	13/125 or 250	4	64	Yes
VAC17KS	C17	18/2	10/125 or 250	4	66	Yes
VAC13CS, VAC13AU, VAC13AD		18/3	10/250	4	68	Yes
APC7KC	C7	18/2	2.5/125	10	1	Yes
APC13HC	C13	18/3	10/125	10	2	Yes
MFC7S	C7	18/2	2.5/125	10	3	Yes
APC13HJ	C13	18/3	10/125	10	4	Yes
APC7HB	C7	18/3 (Functional Ground)	2.5/125	10	5,6	Yes
VCS3KS	Non- Stanard	18/3	2.5/125 or 250	10	7	Yes
VAS3KS	Non- Stanard	18/3	2.5/125 or 250	10	8	Yes
APC7J	C7	18/2	2.5/125	4	67	Yes
DLC5CS3	C5	18/3	7/125	10	9	Yes
VNC7S	C7	18/2	7/125	10	10	Yes
VNC5S	C5	18/3	2.5/125 or 250	10	11	Yes
VNC5FS	C5	18/3	2.5/125 or 250	10	12	Yes
VAC13CS, VAC13AU, VAC13AD	C13	18/3	10/250	4	68	Yes
VNC13S	C13	18,17,16/3	10,12,13/125 or 250	10	13	Yes
<b>VNC7A</b>	<b>C7</b>	<b>18/2</b>	<b>7/125</b>	<b>10</b>	<b>14</b>	<b>Yes</b>

## NONSTANDARD CONFIGURATION

Cat. No.	Config.	Cord AWG	Electrical A/V	Sec.	Fig.	CUL
PHX-949	N/A	18,17/2	10,10/125	4	22	Yes
SR5008	N/A	16/3	13/125	4	33	Yes
DLC5A3	N/A	18/3	2.5/125	4	34	Yes
DLC5SA3	N/A	18/3	2.5/125	4	34A	Yes

## CORD SPLICES:

Cat. No.	Config.	Cord AWG	Electrical A/V	Sec.	Fig.	CUL
497-0420299	N/A	18,16/3	10,13/125	6	1,3	Yes
7594	N/A	18,16,14/3	10,13,15/250	6	2	Yes
Duo-Cord	N/A	18,16,14/3	10,13,16/125 or 250	6	4	Yes
<b>DUO-CORD-B</b>	<b>N/A</b>	<b>14/3</b>	<b>16/125 or 250</b>	<b>6</b>	<b>6</b>	<b>Yes</b>
Trident	N/A	18,16,14/3	10,10,10/250	6	5	Yes